

This example will add the Vero Beach Talk Group to the Vero Beach DMR Repeater

Click General

Enter Radio Name (Your Call) *If you do not have an ID go here:* register.ham-digital.org

Enter Radio ID (your DMR #)

Bottom Right of the General Screen

Intro Screen

Intro Screen Line 1=(Your Name)

Intro Screen Line 2=(Your Call)

Digital Contacts

Add

Enter Contact Name

Enter Call Type=Group

Enter Call ID

Call Receive=No

Channels Information

Right Click>add

Enter Channel Name=(Vero Beach 111209)

Enter RX Freq=444.350

Enter TX Freq=449.350

Admit Criteria=Color Code

Contact Name=(Talk Group)-*Populated earlier from Digital Contacts*

Color Code=(1) (Depends on Repeater)

Repeater Slot=(2) (Depends on Repeater Talk Group Assignment)

Under the Digital Data section>Check the following: Private Call Confirmed, Data Call Confirmed, Compressed UDP Data Header

Leave GPS System at None

Zone Information

Right Click>Add

Click the Zone(x)tab

Zone Name=(rename Zone(x) to what you prefer

From the Available Channel, left side, select Channel desired

When highlighted, click add

Highlighted Channel move to Channel Member

File>save>(desired filename)

Turn radio off>connect programming cable>turn radio on>wait 20 seconds

Program tab>Write Data>Click OK

Radio should receive data>turn radio off>remove cable>turn radio on

Test for new code plug and /or changes to existing code plug.